Software Configuration Instructions for Digital Doc Iris Intraoral Camera and Patterson Eaglesoft/Imaging

۲	Patterson Imaging						
File	Edit View Image	Effe <u>c</u> ts	<u>T</u> ools	<u>A</u> ctivities	<u>L</u> ists	<u>R</u> eports	<u>W</u> indow
	General Preferences		>	-	50		6
	Ne <u>w</u>	• a	anner	Save A	Acquire	E-Mail	Print (
	Open As Document						
뤔	Open Cascaded						
	Open Tiled Horizontally						
	Open Tiled Vertically						
6 24	Browse Images	. 1					
E	Save	- 1					
X	Delete						
¢	Reload						
_	-	- 1					
~	Import Schick Images	D					
с£.	Evport						
	EXPOIL	I					
_	DICOM						
	<u>E</u> -Mail						
~~ <u>~</u> =	E- <u>M</u> ail All						
8	Print	- 1					
a	Print All						
4	Print Custom						
A	Print 1:1 (Actual Size)						
	Printer Administration						

1. From the Patterson Eaglesoft/Imaging home screen, select **File**, then **Preferences/General Preferences**.

Preferences × • 🧬 General 🟹 Spell Checking 📕 X-ray 🚱 SmartDoc 🖌 <u>o</u>k 🕼 Images X <u>C</u>ancel General Defaults * Default Device: (None) • ✓ Use Auto Acquire ✓ Use AutoTake ** Use Exposure Advisor Use Retake Comparison Use scanner default intervace AutoTake only affects Schick USB Sensors Use Exposure Advisor Template Defaults * ScanX Template: (None) Scanner Template: (None) -• Video Template: (None) -Digora Optime Template: (None) -Device Properties: * Scanner Video Schick Panoramic Sigma Sensor Orthopantomograph Þ * Indicates workstation specific preference < Back Next >

Intraoral Camera and Patterson Eaglesoft/Imagin	g										
File Falle View, Jacober Filester Texte Antibiliter Linke December Minatory (
Preferences	×										
🔗 General 🛛 😨 Spell Checking 🔅 Images 📃 🔍 Xray	✓ <u>D</u> K										
General Defaults *	X Cancel										
Default Device: (None)											
Use Exposure Advisor Use Auto Acquire Use Retake Comparison Use scanner default interface V Use Auto Take ** ** Auto Take only affects Schick USB Sensors											
Template Defaults *											
ScanX Template: (None) Scanner Template: (None)											
Video Template: (None)											
Digora Optime Template: (None)											
Device Properties: *											
Scanner Video											
Schick Panoramic Sigma Sensor											
Orthopantomograph											
A											
* Indicates work station specific preference											
< Back Next >											

2. Select the X-Ray tab inside the Preferences Window.

🧬 General	🟹 Spell Checking	🔐 Images	📮 X-ray	🛃 SmartDoc	🖌 🛛 К
General Defaults	1 (X <u>C</u> ancel
Default Device:	None)	~			
Use Expos	ure Advisor e Comparison 📃 Use s	canner default interfa	v Use ve v Use	Auto Acquire AutoTake **	
Template Defa	ideo Capture Properties			×	
ScanX Templa	* Capture Card: Standar	d Windows Driver Mo	del Device 🛛 🔻	Save	
Video Templal	* Default Device: Iris		•	Cancel	
Device Properti	Image Quality *				
	Min		Max		
Orthopantomog	in Compression				
L				0	
Indicates workst	ation specific preference		< B	ack Next >	
					J

4. For Capture Card, select **Standard Windows Driver Model Device**. For Default Device, select **Iris**. Select **Save**.

3. Select the **Video** button.